

# Instruction Manual For Sequential Timer

**MODEL: WD-VIII - ver 1.0**

Customer: \_\_\_\_\_ RIECO INDUSTRIES LTD \_\_\_\_\_

Project: \_\_\_\_\_ KRUPP (SHAH CEMENT) \_\_\_\_\_

Reference: \_\_\_\_\_

## Contents:

<b>Sr. No.</b>	<b>Topic</b>	<b>Page No.</b>
Section 1.	<b>Introduction</b>	<b>3</b>
Section 2.	<b>Operation</b>	<b>4</b>
Section 3.	<b>Optimizing the Cleaning Cycle</b>	<b>5</b>
Section 4.	<b>Installation and Wiring</b>	<b>6</b>
Section 5.	<b>Connection Description - Main PCB</b>	<b>7</b>
Section 6.	<b>Connection Description –Cascade PCB</b>	<b>8</b>
Section 7.	<b>Connection Description</b>	<b>9</b>
Section 8.	<b>Description</b>	<b>10</b>
Section 9.	<b>Technical specifications</b>	<b>11</b>
Section 10.	<b>Technical specifications</b>	<b>12</b>

# Section 1

## **Introduction:**

The bag filter is one of the most effective and efficient pollution control equipment and the sequential timer can be used to maximize its performance. The efficiency and reliability of bag filter, longer bag life, lower consumption of electrical power and economical usage of compressed air can be achieved only with the help of fine-tuning of the cleaning cycle. At same time the timer has got ability to monitor the functionality of Pulse Solenoid Valve in the form of annunciation system to point defective operation. The sequential timer has a complete close loop control over the cleaning cycle that does not need any human intervention for ensuring optimized, satisfactory and trouble free operation.

## **The Sequential Timer offers following features:**

The cleaning is initiated upon reaching 'HIGH' DP and stopped upon achieving 'LOW' DP. With this arrangement you stand to get following advantages:

**Saving in compressed air:** As the cleaning is done based on the differential pressure feed back, the compressed air is used only when it is required. With this the compressed air wastage is eliminated.

**Extension of the bag life:** As the cleaning cycles get restricted to a minimum required, the flexing cycles of the bags are reduced. This directly enhances the bag life.

**Saving in the power consumption of the fan motor:** With the control on the DP, the system curve can be maintained in the region, where the fan efficiency is at it's highest. With this the saving in the power consumed in the fan motor can be achieved.

**The timer with Low DP Time out Facility:** This timer stops pulsing after time out set on trim pot (P2) on going to low DP and ensures the complete cleaning of bags on stoppage (closure)of bag house operation & stores the last out put it had energized in the memory. When the DP reaches high and the purging is reinitiated, it starts from the subsequent out put. Thus the 'OVER BEATING' of the bags from the initial rows is avoided. This saves the bags from initial rows from an early failure.

The auto flushing mechanism contains a solenoid controlled diaphragm valve that operates periodically and flushes the tubing of the differential pressure gauge. This ensures elimination of a false signal from the D.P. gauge.

**Note:** The Auto flushing mechanism and the Differential Pressure Switch are optional and may not form part of this supply unless ordered. However the potential free input for the differential pressure switch is provided with the timer card and that can be used for its integration with differential pressure digital feed back.

## Section 2

### Operation:

The function of this timer is to send the pulses to the solenoid valves and, intern, trigger the diaphragm valves for sequential cleaning of the bag filter. The POWER ON GREEN LED (**L3**) glows when power is connected to the power input and it indicates healthy condition of the power supply. In case the supply fuse blows out RED LED will glow indicate blown fuse (F1 2AMP. )

The duration of the cleaning pulse is known as ON TIME and is set usually to 40 mSec. This setting may need to be changed depending on the response time of the solenoid valves. For severe cleaning the ON time may be increased to 100 mSec. This type of cleaning is recommended only during shutdowns.

The ON TIME potentiometer range is from 20 mSec to 200 mSec.

The duration between the two pulses is known as OFF TIME.

The OFF TIME potentiometer range is from 2 Sec to 60 Sec.

This indicated by clock RED L ED (**L14**)

Each of the output is provided with an LED indicator. The LED indicator remains in ON condition for the duration of the corresponding pulse. (**L7 to L13 & L15,L16**)

The connections to the solenoid valve are taken through the Phoenix Terminal strip where SOL COMM. is one terminal wherein the pulse peak current flowing out through this terminal is monitored via current transformer (**CT1**) for "NO" solenoid operation /connection. A fault relay (**RLY1**) will operate in case of malfunction indicted by RED LED (**L1**) on .This relay is latching type has to be RESET to declare (accept )the fault , so that circuit is ready to indicate next possible fault if any.

The air header provided with LOW pressure switch ,as sensor input, is used for "CONTINUOUS "Solenoid on fault monitoring via annunciation system. RED LED (**L4**) indicates low header pressure. Annunciation Relay on indicated by RED LED (**L1**)

A closed contact connected across the Differential Pressure input RED LED (**L6**) terminals starts the sequential cleaning and an open contact across these terminals stops the cleaning. The restart of the cleaning takes place once the Differential Pressure input senses a close contact and it then starts cleaning from the subsequent out put from where it has stopped.

## **Section 3**

### **Optimizing the cleaning cycle:**

#### **Setting the limits for cleaning to protect the bags:**

The optimization of the cleaning cycle is accomplished with the help of a differential pressure gauge. The gauge sends a feed back to the sequential timer to stop/ restart the cleaning cycle. The potential free contact used by the Sequential Timer closes on reaching HIGH DIFFERENTIAL PRESSURE and opens on reaching LOW DIFFERENTIAL PRESSURE across the bags.

It is important to maintain a layer of dust (DUST CAKE) on the surface of the bags. This protects the fabric of the bags from plugging due to fine dust. It is important to maintain the differential pressure to a low value in order to maintain adequate suction at the pick up point of the ventilation systems.

The above two aspects decide the TOTAL static pressure drop across the ventilation system.

It need to be noted that the static pressure drop across the dampers, ducts and various bends that the gas has to negotiate within the bag filter is almost constant for a given process. In this case the static pressure drop of the total ventilation system can vary only with the pressure drop across the bags.

Hence the pressure drop can be adjusted in order to run the fan in the most efficient region by allowing the desired amount of dust cake on the surface of the filter bags.

From the above statements it can be established that optimization of the cleaning cycle need not result in the minimum differential pressure across the bags but it should ensure that the fan operates in its most efficient region.

#### **Usage of FAN CURVES to decide the desired differential pressure:**

With the help of the FAN CURVES the desired point of operation can be decided and the differential pressure gauge set points can be adjusted to provide a narrow band of operation around the desired differential pressure level. **Narrower the band of operation lesser is the variation in the fan operation which, intern, would ensure a steady running of the process.**

#### **Avoid reentrainment of the dust with staggered cleaning:**

The cleaning sequence can be made more effective by minimizing the reentrainment of the dust. It needs to be noted that the permeability of a cleaner bag is higher than the bag under cleaning. Thence the gas shall have a tendency to flow through a cleaner bag than a bag with thicker dust cake. If the cleaning is done in a sequential manner then the dust have a tendency to fly off with the gas flow to the adjoining cleaner row of bags. This phenomenon shall increase the indirect dust load on the bag filter and shall need higher frequency of cleaning

With the help of staggered cleaning the reentrainment can be reduced as the cleaner row of the bags and the row of bags that is under cleaning are not closed to each other. The recommended cleaning sequence for a typical 10-row bag filter shall be 1,6,3,8,5,10,2,7,4,9 and repeat. The connections of the sequential timer outputs and the solenoid valves can be wired accordingly, to provide staggered cleaning.

## Section 4

### Installation and wiring:

#### **Installation:**

The timer is shipped with an enclosure to suit the site conditions( weather proof, IP54 or IP55). The timer is to be mounted by the customer at a location, which is easily accessible, free from vibration, protected from direct Sunlight and with an ambient of less than 50°C.

#### **Channel out put selection via 10 way DIPswitch (Main PCB) and 8 way DIPswitch (Cascade PCB) :**

The select channels (programming) dip switch is used to avoid the delay between energisation of last solenoid valve and the first solenoid valve if lesser outputs are used. The programming dipswitch can be placed to appropriate location as marked on the board.

#### **Example:**

For setting Say 12 output put the switch for channel selection for main PCB is to be set on all ten switches OFF so that it will give output of nine & put channel selection switch of cascade PCB on "4" so that only three channels are selected. So point to be noted is that **always put the select channels dipswitch on position one ahead of required one.**

**IMPORTANT NOTE:** with Dipswitch setting Never Put Two switches "ON" at a time. In this case the first switch put ON will not give corresponding Solenoid output.

#### **Wiring:**

The following description should be read with reference to the connection diagram provided

#### **Step by step wiring Descriptions**

- 1> Follow the electrical wiring diagram provided (X'1003/1, Rev.2 03.12.2000)  
TWO PAGES.
- 2> There are three types of main connections for controller
  - A> power in or **Mains Input**
  - B> process control **sensor inputs & feed back alarm o/p**
  - C> **Controller output** (power connections) for process requirement (110 V AC solenoid power in this case)

## Section 5

### Connection Description:

**TS6** – **Mains input** 3way terminal strip

**COLD : 110V AC**  
**LIVE : 110V AC**  
**Earth**

**TS5**- **Alarm /Fault relay** OUTPUT Potential free 10A, 110 Volts

**N/O**  
**POLE**  
**N/C**

**TS2** –**Header Pressure N/C** pressure switch on delay provided for 5 secs

**N/C**  
**POLE**

**TS1**- **On panel N/O switch to reset** the fault Relay if operated  
Indicating faulty sol. Operation

**N/O**  
**N/O**

**TS8** –Bag house **LOW DIFFERENTIALPRESSURE** connection to trigger  
time out pulsing before stopping Dust collection system.

**N/C**  
**N/C**

**TS7**- not used in this System

**TS9 to TS15** – **POWER OUTPUT**

**SOL1** SOLENOID NO. 1 CONNECTION  
**COM**

**SOL2** SOLENOID NO. 2 CONNECTION  
**COM**

**SOL3** SOLENOID NO. 3 CONNECTION  
**COM**

**SOL4** SOLENOID NO. 5 CONNECTION  
**COM**

## Section 6

**SOL5 SOLENOID NO. 6 CONNECTION  
COM**

**SOL6 SOLENOID NO. 6 CONNECTION  
COM**

**SOL7 SOLENOID NO. 7 CONNECTION  
COM**

**SOL8 SOLENOID NO. 8 CONNECTION  
COM**

**SOL9 SOLENOID NO. 9 CONNECTION  
COM**

**TS16- COMMON CONNECTION FOR CASCADE PCB**

**NEXT COMMON  
NEXT +110VAC**

### **ELECTRIC ALCONNECTIONS TO CASCADE**

**TS1- +110 VOLT input 2 way terminal strip**

**PREVIOUS +110V AC  
PREVIOUS COMMON**

**TS2- not used in this System**

**TS3 to TS9 – POWER OUTPUT**

**SOL1 SOLENOID NO. 1 CONNECTION  
COM**

**SOL2 SOLENOID NO. 2 CONNECTION  
COM**

**SOL3 SOLENOID NO. 3 CONNECTION  
COM**

**SOL4 SOLENOID NO. 3 CONNECTION  
COM**

**SOL5 SOLENOID NO. 5 CONNECTION  
COM**

**SOL6 SOLENOID NO. 6 CONNECTION  
COM**

**SOL7 SOLENOID NO. 7 CONNECTION  
COM**

## **Section 7**

**SOL8 SOLENOID NO. 8 CONNECTION  
COM**

**TS10- Power to next cascade**

**NEXT COMMON  
NEXT 110V**

### **LED INDICATION ON MAIN (MASTER) PCB EXPLANATIONS**

**L1 ALARM RELAY ON  
L2 MAINS FUSE BLOWN  
L3 MAINS FUSE OK  
L4 HEADER PRESSURE LOW  
L5 24 SOLENOID POWER OK  
L6 DP ACROSS PLENUM & HOUSING LOW IN DUST COLLECTOR SYS.  
L7-L13,L15,L16 1 TO 9 SOLENOID ON INDICATION  
L14 SOLENOID ON AND OFF CLOCK**

## Section 8

### **Description:**

The line and neutral terminals on the timer board are to be wired to 110 V 50 Hz power source unless otherwise specified.

Outputs 1 to 17 of the sequential timer (Main PCB + Cascade PCB) are to be connected to one of the connections of the corresponding solenoid valve and the other connection of all the solenoid valves are to be terminated to the SOL. COM. terminal.

In case of a bag filter with solenoid valves more than 17 or with multiple pressure headers, more than one solenoid valve can be connected to the timer out puts.

### Example:

Bag filter with 29 solenoid valves: The 1<sup>st</sup>, 11<sup>th</sup> and 21<sup>st</sup> solenoid valves can be grouped together to be connected to output no one, 2<sup>nd</sup>, 12<sup>th</sup> and 22<sup>nd</sup> solenoid valves can be grouped together and connected to another out put and so on. The last out put can be connected to 10<sup>th</sup> and 20<sup>th</sup> solenoid valves.

In case the bag filter has 18 solenoid valves then the same can be divided in six groups of 3 and the programming jumper can be put in position 7 as marked on the timer board dip switch.

## Section 9

### **Technical specifications:**

1. **Input Power:** 110 V ac +20% - 10%, 50Hz or 60 Hz 2 Amp (Max)
2. **Output Power:** 24 Triac outputs, 2 Amp (Max) +110V AC.
3. **Control Signal:** Potential free signal from differential pressure LOW DP switch.  
(To be ordered separately) Close to Start  
Open to Stop
4. **Time out period (pot P2):** 25 secs to 30 min  
For DP switch control  
(after stopping dust collector FAN system )
5. **Air Header Low Pressure :** Potential free signal from differential pressure LOW Switch  
(To be ordered separately) Close to normal  
Open to fault
6. **Time out period for header:** 5 secs fixed built in the unit  
pressure switch
7. **Fault / Alarm Relay output :** Potential free 10A, 110 VAC Resistive  
For Solenoid Malfunction
8. **Toroidal Transformer for powering :** Primary 0-110, 0-110VAC, 50 Hz  
circuitry & solenoid DC energy Secondary 6-0-6-12V, 200mA
9. **Each single pulse is monitored :** Alarm relay output for fault O/P.  
for Solenoid healthy o/p for no is provided  
connection , for short circuit, for  
blown fuse F2
10. **Zero crossing detection for :** Provided as Standard Feature  
Triac trigger
11. **Timing for Pulse on & off period :** ON- 20 mSec to 200 mSec  
OFF- 2 Sec to 60 Sec
12. **Diagnostic & useful function specific:** Incorporated LED's on PCB
13. **Connection wire between MAIN :** 9 Pin "D" type connector using  
PCB & CASCADE PCB multicore flexible Wire

## Section 10

### Technical specifications:

14.MAIN PCB to chassis spacers :	4 nos.----- M4 x 25
15.Support Spacers :	4 nos. -----M4 x 25
16.MAIN PCB Size :	276mm x 200mm
17.MAIN PCB Mounting :	265 mm x 190 mm
18.Cascade PCB to Chassis Spacers :	4 nos.----- M4 x 25
19.Support Spacers in Cascade PCB:	2 nos. -----M4 x 25
20.CASCADE PCB Size :	200mm x 177mm
21.CASCADE PCB Mounting :	190 mm x 166 mm
22.Enclosure:	IP-55 enclosure, suitable for Out door duty, With epoxy polyester coating (Admiral gray)
23.Differential pressure switch:	0 to 250 mm WC with $\pm$ 2% accuracy over the entire range. (CLIENT'SDCOPE/OPTION) with settings for HIGH and LOW DP.

### Points to be noted for timer DO & DON'T DO things

- 1> Dip switch setting Never Put Two switches on at a time the first switch put on will not give corresponding o/p.
- 2> For setting Say 12 output put the switch for channel selection for main PCB is to be set on all ten switches OFF so that it will give o/p of nine & put channel selection switch of cascade PCB on 4 so that only three channels are selected. So point to be noted is that always put the Dipswitch on position one ahead of required one.
- 3> Before energizing the timer check fuses are in secured position & tight.
- 4> Connect live to live & cold to cold connection.

### Watch for Diagnostic LEDS

- 1> Fuse F1 is OK green L3 will light on power on. Other wise Red LED will glow indicating that fuse is blown or not fitted properly.
- 2> Led L5 will indicate healthiness of 24-volt power used as pulsed dc for solenoid energisation
- 3> If fuse F2 is loose or blown off output LEDS from L7 to L16 will pulse very weakly (this is because of 5 volt power added to 24 volt pulsed dc for Triac triggering (BT 136-6)
- 4> Cascading of slave PCB has also function Indicators Like +12v POWER LED1, Clock RED LED L9, Healthy +24 volt Power L1 and L3 to L11 for solenoid out put SOL2 to SOL8

[Down Load](#) Manual

**Email to :**